

CHP Max Headend Optics Platform

CHP-R2RRX*-30-S
CHP-2RRX*-30-S
Redundant/Non-Redundant
Dual Return Path Receiver

FEATURES

- 300 MHz return path bandwidth meeting DOCSIS® 3.1 requirements
- Optimize headend and hub efficiencies with industry leading density and low power consumption
- Front or Rear Fiber options maximize cabling efficiency
- Improve system uptime with automatic failover option
- Configure, monitor, and manage with CORView™ Element Management System



PRODUCT OVERVIEW

The CHP Dual Return Path Receiver is an integral part of a flexible return path system. Designed to operate as either a stand-alone or redundant module, the CHP Dual Receiver allows operators to increase their network capacity while reducing operational power. With support for up to 300 MHz of return bandwidth, the CHP Dual Receiver is an ideal choice for supporting future DOCSIS 3.1 band splits without out having to upgrade receivers.

The CHP Dual Return Path Receiver accepts two optical inputs into a single-wide module, which supports up to 20 receivers in a single 2RU CHP chassis and up to 400 receivers in a standard 40RU rack. As operators add bandwidth to their networks, the CHP Dual Receiver can help them to achieve a migration path to DOCSIS 3.1 bandwidth. There is a front or rear fiber SC/APC connector option for the CHP Dual Return Path Receiver.



The CHP Dual Receiver is available in both redundant and non-redundant configurations. The redundant model protects both the optical path and vital hardware for VoIP, business data services, and other critical applications. For additional protection, the redundant model’s integral optical and RF switches alternate between diverse paths when the receiver detects an optical path module hardware fault. In these instances, switch time is less than 50 milliseconds. Operators can pair redundant and non-redundant modules in either the same CHP chassis or in a spare chassis up to 6 meters away.

The CHP Dual Receiver offers high RF output with excellent power efficiency, typically consuming less than 3 Watts per RF channel. The modules are hot-swappable to ensure minimal loss of uptime. The receiver’s Craft Graphical User Interface (GUI) provides local monitoring, configuration control, and firmware downloads, while the System Management Module (SMM) provides local and remote IP access to the Craft GUI, firmware downloads, and the SNMP HMS interface.

OPTIONS

Redundant or Non-Redundant
CORView Element Management System

RELATED PRODUCTS

CHP Chassis	Optical Patch Cords
Power Supplies	Optical Passives
Management Module	Installation Services

Ordering Information

Part #	Model #	Description
803109	CHP-2RRXF-30-S	CHP-2RRXF-30-S: Family: CHP Max5000; Type: Dual Channel 300 MHz Return Receivers; Front Fiber; Optical Connector: SC/APC
803110	CHP-2RRXR-30-S	CHP-2RRXR-30-S: Family: CHP Max5000; Type: Dual Channel 300 MHz Return Receivers; Rear Fiber; Optical Connector: SC/APC
803111	CHP-R2RRXF-30-S	CHP-R2RRXF-30-S: Family: CHP Max5000; Type: Redundant Dual 300 MHz Return Receivers; Front Fiber; Optical Connector: SC/APC
803112	CHP-R2RRXR-30-S	CHP-R2RRXR-30-S: Family: CHP Max5000; Type: Redundant Dual 300 MHz Return Receivers; Rear Fiber; Optical Connector: SC/APC

GENERAL SPECIFICATIONS		
	CHP-R2RRX*-30-S	CHP-2RRX*-30-S
Optical Specifications		
Input Wavelength Range	1260 to 1620 nm	1260 to 1620 nm
Optical Input Range	-20 to 3 dBm	-20 to 3 dBm
Optical Return Loss	55 dB	55 dB
RF Specifications		
RF Output Bandwidth	5 to 300 MHz	5 to 300 MHz
RF Output Level, min. per channel (Note 1)	40 dBmV	40 dBmV
Flatness, peak-to-valley	±0.75 dB with respect to gain slope	±0.75 dB with respect to gain slope
Gain Slope	±1.0 dB	±1.0 dB
RF Gain Adjustment Range (Note 2)	0 to -31.5 in 0.5 dB steps	0 to -31.5 in 0.5 dB steps
RF Output Return Loss, min.	16 dB	16 dB
RF Testpoint	-20 ± 0.5 dB	-20 ± 0.5 dB
Performance Specifications		
Equivalent Input Noise	<4.5 pA/Hz ^{0.5}	<4.5 pA/Hz ^{0.5}
Maximum Peak NPR Variation	4 dB	4 dB
Noise-to-Power Ratio (NPR)/Dynamic Range	40/13 dB	40/13 dB
BER Dynamic Range	>40 dB	>40 dB
Optical Input to RF Output Terminated Isolation	≥60 dB	≥60 dB
Channel-to-Channel Isolation	5 to 300 MHz@60 dB	5 to 300 MHz@60 dB
Redundant Switching Time	50 ms	N/A
Power Consumption	7 W	7 W
Mechanical Specifications		
Dimensions (W x H x D) in (cm)	1.25 x 3.44 x 18.5 in (3.18 x 8.74 x 46.99 cm)	1.25 x 3.44 x 18.5 in (3.18 x 8.74 x 46.99 cm)
Environmental Specifications		
Operating Temperature Range	0 to 50°C (32 to 122°F)	0 to 50°C (32 to 122°F)
Operating Humidity, Non-condensing	10 to 90%	10 to 90%

Notes:

- 1. RF output is based on -9 dBm optical input at 7% OMI.
- 2. The attenuator for each channel in the modules may be adjusted in 0.5dB steps from 0 to 31.5 dB.

Customer Care

Contact Customer Care for product information and sales:

- United States: 866-36-ARRIS
- International: +1-678-473-5656

Note: Specifications are subject to change without notice.

Copyright Statement: ©ARRIS Enterprises, Inc. 2015 All rights reserved. No part of this publication may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from ARRIS Enterprises, Inc. ("ARRIS"). ARRIS reserves the right to revise this publication and to make changes in content from time to time without obligation on the part of ARRIS to provide notification of such revision or change. ARRIS and the ARRIS logo are all registered trademarks of ARRIS Enterprises, Inc. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and the names of their products. ARRIS disclaims proprietary interest in the marks and names of others. The capabilities, system requirements and/or compatibility with third-party products described herein are subject to change without notice.

CHP 2RRX30_29SEP14

(rev 09-2014)